



High power contactor, TeSys Giga, 4 pole (4NO), AC-1 <=440V 250A, advanced version, 24...48V wide band AC/DC coil

LC1G1154BEEA

EAN Code: 3606481922526

Main

Range	TeSys
Range of product	TeSys Giga
Product or component type	Contactor
Device short name	LC1G
Contactor application	Power switching
Utilisation category	AC-1 AC-5a AC-5b AC-6a AC-6b DC-1 DC-3 DC-5
Poles description	4P
[Ue] rated operational voltage	<= 1000 V AC 50/60 Hz <= 460 V DC
[le] rated operational current	250 A (at <40 °C) at <= 1000 V AC-1
[Uc] control circuit voltage	2448 V AC 50/60 Hz 2448 V DC
Control circuit voltage limits	Operational: 0.8 Uc Min1.1 Uc Max (at <60 °C) Drop-out: 0.1 Uc Max0.45 Uc Min (at <60 °C)

Complementary

[Uimp] rated impulse withstand voltage	8 kV
Overvoltage category	Ш
[Ith] conventional free air thermal current	250 A (at 40 °C)
Rated breaking capacity	1040 A at 440 V
[Icw] rated short-time withstand current	1.1 kA - 10 s 0.64 kA - 30 s 0.52 kA - 1 min 0.4 kA - 3 min 0.32 kA - 10 min
Associated fuse rating	125 A aM at <= 440 V for motor 125 A aM at <= 690 V for motor 315 A gG at <= 690 V
Average impedance	0.00018 Ohm

[Ui] rated insulation voltage	1000 V
Power dissipation per pole	10 W AC-1 - Ith 250 A
Compatibility code	LC1G
Pole contact composition	4 NO
Auxiliary contact composition	1 NO + 1 NC
Irms rated making capacity	1560 A at 440 V
Coil technology	Built-in bidirectional peak limiting
Mechanical durability	8 Mcycles
Inrush power in VA (50/60 Hz, AC)	290 VA
Inrush power in W (DC)	220 W
Hold-in power consumption in VA (50/60 Hz, AC)	10 VA
Hold-in power consumption in W (DC)	5.7 W
Operating time	4070 ms closing 1550 ms opening
Maximum operating rate	300 cyc/h AC-1
Connections - terminals	Power circuit: bar 2 - busbar cross section: 25 x 6 mm Power circuit: lugs-ring terminals 1 185 mm² Power circuit: bolted connection Control circuit: push-in 1 0.22.5 mm² - cable stiffness: solid stranded without cable end Control circuit: push-in 1 0.252.5 mm² - cable stiffness: flexible with cable end Control circuit: push-in 2 0.51.0 mm² with cable end Control circuit: push-in 0.752.5 mm² - cable stiffness: solid stranded without cable end Control circuit: push-in 0.752.5 mm² - cable stiffness: flexible with cable end
Connection pitch	35 mm
Mounting support	Plate
Standards	EN/IEC 60947-4-1 EN/IEC 60947-5-1 UL 60947-4-1 CSA C22.2 No 60947-4-1 JIS C8201-4-1 JIS C8201-5-1
Product certifications	CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL
Tightening torque	18 N.m
Height	255 mm
Width	143 mm
Depth	193 mm
Net weight	5.1 kg
Environment	
IP degree of protection	IP2X front face with shrouds conforming to IEC 60529 IP2X front face with shrouds conforming to VDE 0106
Ambient air temperature for operation	-2560 °C
Ambient air temperature for storage	-6080 °C
Mechanical robustness	Vibrations 5300 Hz 2 gn contactor open Vibrations 5300 Hz 4 gn contactor closed Shocks 10 gn 11 ms contactor open Shocks 15 gn 11 ms contactor closed

Colour	Dark grey
Protective treatment	тн
Permissible ambient air temperature around the device	-4070 °C at Uc
Packing Units	
Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	25.0 cm
Package 1 Width	26.0 cm
Package 1 Length	38.0 cm
Package 1 Weight	6.376 kg
Unit Type of Package 2	S06
Number of Units in Package 2	6
Package 2 Height	75.0 cm
Package 2 Width	60.0 cm
Package 2 Length	80.0 cm
Package 2 Weight	48.256 kg
Offer Sustainability	
Sustainable offer status	Green Premium product
REACh Regulation	REACh Declaration
EU RoHS Directive	Compliant EU RoHS Declaration
Mercury free	Yes
China RoHS Regulation	China RoHS declaration
RoHS exemption information	Yes
Environmental Disclosure	Product Environmental Profile
Circularity Profile	End of Life Information
PVC free	Yes
Halogen content performance	Halogen free plastic parts product

Contractual warranty

Warranty 18 months

Product datasheet

LC1G1154BEEA

Installation

Installation Videos

TeSys Giga - How to install the auxiliary contact block

TeSys Giga - How to install and remove remote wear diagnosis module

TeSys Giga - How to install mechanical interlock kit

TeSys Giga - How to replace control module

TeSys Giga - How to replace switching modules

TeSys Giga - How to assemble change-over solution

Recommended replacement(s)